

CD PLAYER

## CD14



In 1989, Rotel confirmed its digital audio expertise with the launch of the RCD-855 CD player. The press was overwhelming in its praise, one critic going so far as to call it "The steal of the century", and since then Rotel has never looked back. The CD14 design begins with a carefully engineered power supply

to ensure separate, ripple-free voltage and current to both digital and analogue circuits. It maintains the same clean lines and intuitive operation as the other 14 series models, while demonstrating an uncanny ability to resolve even the smallest musical details in a recording.





## CD PLAYER

## CD14



## **SPECIFICATIONS**

Total Harmonic Distortion + Noise

Intermodulation Distortion Frequency Response (± 0.5 db)

Channel Balance
Phase Linearity

Channel Separation
Signal to Noise Ratio
("A" weighting)

("A" weighting) **Dynamic Range** 

Digital to Analog Converters

**Analog Output Impedance** 

Digital Output

Digital Output

Load Impedance

0.002% @ 1kHz

0.002% @ 1kHz 20-20,000Hz ± 0.5 db ± 0.5 degree > 115 dB @ 10 kHz

> 118 dB

> 99 dB

Wolfson 24 bit/192kHz

DAC

100 Ohms

0.5 Volt, Peak to Peak

75 Ohms

General

Power Requirements (AC)

Europe
USA
Power Consumption

Standby Power Consumption

Finishes

 $\textbf{Dimensions} \; (\mathsf{W} \; \mathsf{X} \; \mathsf{H} \; \mathsf{X} \; \mathsf{D})$ 

Front Panel Height
Weight (net)

230V, 50Hz

120V, 60Hz 15 watts < 0.5 watts Silver and Black

430 x 98 x 312mm 17" x 3 7/8" x 12 5/16"

80mm, 3 1/8" 5.9kg, 13 lb

Get the most out of your CD collection with Rotel's compact disc players. See more at



