



Smart Soundbox 3



Туре	Multiroom-speaker
Engineering Principle	Bassreflex with passive membrane
Systempower	120 Watts
Frequency response	4030.000 Hz
Crossover frequency	3000 Hz
Passive membrane	2x (100 x 57mm / 3.9" x 2.2"), metal, wave surround
Mid-/Woofersystem	1x 95mm (3.7"), aluminium
Tweeter	1x 19mm (0.75"), fabric
Connection	1 x Analog (3.5 mm Stereo jack) 1 x Ethernet (LAN)
Features	"Chromecast built-in for Audio" support Spotify connect support Bluetooth® 4.0 interface WLAN 802.11ac 2.4 /5GHz Bass, midrange and treble control LED display in front of housing
Special Features	Easy installation - one cable to the power supply IR learning function - controllable with TV / system remote control Automatic switch-on and switch-off ECO Mode - selectable power saving mode (On/Off) Bluetooth Select - Selects BT input automatically IR delete function - simplest deletion of unwanted learning functions Equalizer - 3 presets for acoustic adjustment Easy-Pairing - simplest connection with a device Operation as a stereo pair with a second Soundbox 3 possible Operation as surround loudspeaker with a Smart Soundbar or Vento9/3 possible In stereo mode balance can be adjusted In stereo mode, it is possible to adjust the hearing distance Voice function for better speech intelligibility Direct input selection ideal for system remote controls Sleep Timer 3 preset buttons for direct access to playlists and sound settings Hotel Mode (maximum system volume) Auto Play Function - Auto Play for Bluetooth Playback control of Bluetooth and network sources (play/pause) via touch panel (via optional remote additionally title jump forward and backward) Restore factory settings
Warranty	2 years
Dimensions (WxHxD)	12 x 21 x 12 cm (4.4" x 8.3" x 4.4")
Weight	2 kg
Power consumption	0.4 watts
Available accessories	Smart-Remote control LS 3 speaker stand Cantomount U
Carton Content	Smart Soundbox 3 Power cord 1.5 m Short manual Spotify manual
Packaging	29 x 16 x 16 cm (11,4" x 6,3" x 6,3")